

# **BARNSTORM**

## **Light Board Op: Pre-Show and Post-Show Checklist**

### **PRE-SHOW :**

1. In the booth, press the power button on the Board
  - a. The monitors should turn on by themselves; if they don't press the power button on the monitors
2. Turn off Work Lights, Flood Lights and House Lights
3. Type: 1 > FULL > S5 > ENTER
  - a. This will move you into channel check
4. Use the NEXT and LAST buttons to go through every light
  - a. You are checking that all the instruments turn on and are in the right positions
  - b. If you find a problem, take note of what channel is not working and tell the Stage Manager immediately
5. Once through all the lights turn on House Lights to full
6. Click CANCEL to move out of channel check.
7. When instructed to by Stage Manager go into preshow lighting
  - a. GO TO CUE > 1 > ENTER

**You are now in show mode, follow SM's instructions**

# **BARNSTORM**

## **Light Board Op: Pre-Show and Post-Show Checklist**

### **Post-Show:**

1. Once the house is cleared and Stage Manager says you can you can begin shutting off the board
2. Turn the HOUSE LIGHTS knob to full (call Going Bright before doing so)
3. Turn on work lights (call Going Bright before doing so)
4. Type in GO TO CUE > OUT > ENTER
  - a. This will shut off all the show lights, they must be off before you shut off the board
5. Using the mouse click the triangle in the lower right-hand corner of the screen, this will bring up the menu
6. Double click POWER OFF DEVICE
7. It will ask you if you are sure, click YES
8. If it asks you to save for any reason, click NO

**The board is now off, and you can leave when Stage Manager says you are free to go.**

Thank you! <3